

## Wifi Smarthome Socket

EG-PM1W-001

### YOUR SWITCH IS MY COMMAND

- Altijd en overal controle over uw elektrische apparaten: zet apparaten of verlichting eenvoudig aan of uit met behulp van uw smartphone of tablet. Dankzij de ingebouwde wifi repeaterfunctie heeft u altijd optimaal bereik



### Kenmerken

- Slimme programmeerbare Wifi stekkeradapter met ingebouwde wifi-repeaterfunctie
- Schakel aangesloten apparaten aan/uit vanaf de computer, tablet of mobiele telefoon
- Programmeerbare tijdschakelaar met uitgebreide mogelijkheden
- Koppel het inen uitschakelen van het stopcontact aan het openen of sluiten van programma's op de PC, of het starten en afsluiten van Windows
- Eenvoudige bediening via elke computer binnen uw lokale netwerk met de ingebouwde webserver (Via een internet browser)

### Verpakking

Verpakkingshoeveelheid/stuks	20
Volume doos/CUM	0.02634825
Gewicht doos/kg	5.1
Afmetingen productverpakking LxBxH:	80x95x160 mm
Afmetingen transportverpakking LxBxH:	430x285x215 mm
Land van herkomst	CN
Streepjescode	8716309076555
Douanecode	8544429090

### Inhoud verpakking

EG-PM1W-001  
User manual and Quick installation guide  
CD with Power Manager software for Windows

### Certificaat/Certificaten



### Specificaties

Interface: Wireless LAN IEEE 802.11 b/g/n protocols up to 300 Mbps

WLAN repeater mode

Input voltage: up to 250 VAC, 50 – 60 Hz

Maximum load current: 16 A

Maximum power consumption: 2.5 W

Hardware schedule possibilities:

Maximum number of independent hardware schedules 45

Time interval between the events – from 1 minute to 180 days

Loop period indays, hours, minutes or seconds ( single loop period per socket)

Timer accuracy: not more than 2 seconds error per day

Clock synchronisation with NTP server

Dimensions: 108 mm x 76 mm x 55 mm

Net weight: 0.15 kg

### Systeemvereisten

Local area network with a WLAN switch/router  
Any Internet-enabled computer connected to the local area network  
Computer running Windows® 2000/XP/Vist/Windows 7/8 is required for using the Power Manager software (use of this software is not