

Multipresa Programmabile EnerGenie

EG-PM2

YOUR SWITCH IS MY COMMAND

- EG-PM2 is a power outlet strip with advanced power management features. It is possible to individually switch 4 sockets on or off manually via your PC, by timer schedule, or by programmable special events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print)
- Stay in control of all your electrical devices at home or in the office
- Program four sockets individually via your PC or laptop
- An advanced standby-killer for computer peripherals



Caratteristiche

- Accendi e spegni le singole prese direttamente dal tuo pc
- Accendi e spegni le singole prese programmando il timer schedule
- Accendi e spegni le singole prese quando si verifica un determinato evento (ad esempio, avvio di Windows o altre applicazioni, avvio e fine stampa ecc.).
- Il timer rimane attivo anche quando il PC di gestione è spento
- Protezione per bambini
- Fori di montaggio

Confezione

Quantità per cartone, pezzi	10
Volume del cartone, CUM	0.0459885
Peso del cartone, Kg	12.8
Individual package size LxWxH:	465x145x65 mm
Carton size LxWxH:	430x345x310 mm
Paese di origine	CN
Barcode	8716309075565
Customs code	8544429090

Contenuto della Confezione

- EG-PM2
- User manual
- USB cable
- CD with Power Manager software for Windows

Specifiche

Input voltage: up to 250 VAC, 50 – 60 Hz
 Maximum load current: 10 A
 Maximum power consumption: 3.5 W
 Built-in power supply
 Hardware schedule possibilities:
 Maximum number of independent hardware schedules 16
 Time interval between the events – from 1 minute to 180 days
 Timer accuracy: not more than 2 seconds error per day
 Working temperature range: 0 40 Celsius degrees
 Dimensions: 378 x 98 x 55 mm

Certificazioni

