

# EnerGenie Programmable power strip with LAN interface

## EG-PM2-LAN

### YOUR SWITCH IS MY COMMAND

- EG-PM2-LAN is a power outlet strip with advanced power management features. It is possible to individually switch 4 sockets on or off manually via your local network or Internet, by timer schedule, or by programmable special events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print). With your free personal user account on EnerGenie.com you can manage your EG-PM2-LAN via Internet from all over the world, even with your smartphone.
- Stay in control of all your electrical devices at home or in the office
- Program four sockets individually via LAN or Internet
- Switch electric devices on or off with your smartphone, wherever you are
- An advanced standby-killer for computer peripherals
- Perfect solution for security systems , sauna , aquariums, pet habitats, etc.



### Características

- Switch individual sockets on/off manually from your computer
- Switch individual sockets on/off by a programmable timer schedule
- Switch individual sockets on/off whenever a certain software event occurs (e.g. Windows/other software start-up/shutdown, print spooler starting and finishing its job, etc)
- Because of the LAN interface and the built-in web-server, EG-PM2-LAN can be accessed from any computer within your local network (via an Internet browser or Power manager software)

### Embalaje

|                                   |                |
|-----------------------------------|----------------|
| Qtd por caja, pcs                 | 10             |
| Volumen caja, M3                  | 0.047472       |
| Peso caja, kgs                    | 12.72          |
| Medidas cajas individuales LxWxH: | 400x145x65 mm  |
| Medidas caja LxWxH                | 430x345x320 mm |
| Pais de origen                    | CN             |
| Código de barras                  | 8716309075572  |
| codigo de aduanas                 | 8544429090     |

### Contenido de la caja

- EG-PM2-LAN
- User manual and Quick installation guide
- RJ45 cross-over cable (red), RJ45 LAN cable (grey)
- CD with Power Manager software for Windows

### Especificaciones

- RJ45 LAN connector
- Input voltage: up to 250 VAC, 50 - 60 Hz
- Maximum load current: 10A
- Maximum power consumption: 2.5 W
- Built-in power supply
- Power cord: 1.8 m
- Hardware schedule possibilities:
  - Maximum number of independent hardware schedule events - 45 per socket
  - Time setting accuracy in seconds
  - Combine periodical and once events

### Requisitos del sistema

- Local area network with RJ45 sockets
- Any Internet-enabled computer connected to the local area network
- Computer running Windows® 2000/XP/Vista or Windows 7 is required for using the Power Manager software (use of this software is not compulsory)

### Certificados

