

## WiFi Smart Home Socket

EG-PM1W-001

### YOUR SWITCH IS MY COMMAND

- EG-PM1W-001 is an easy to use WiFi Smart Home socket with powerful power management options. It enables you to switch the socket on or off via your home WiFi, Internet, by timer schedule, or by programmable special software events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print). With your free personal user account on EnerGenie.com you can manage your EG-PM1W-001 via Internet from all over the world. The practical and easy to use PowerMan app allows you to control the socket from your smartphone.
- Stay in control of all your electric appliances
- Simply switch devices on or off with your smart phone or tablet
- Built-in WiFi repeater function –Optimal WiFi coverage ensured



### Features

- Intelligent programmable WiFi power socket with built-in WiFi-repeater function
- Switch connected devices on or off with your computer, tablet or smart phone
- Fully featured programmable timer schedule possibilities
- Link on/off switching of the socket to certain software events or Windows start-up/shutdown
- Easy access from any computer within your home network network (via your Internet browser)
- With your free EnerGenie.com user account you will get easy worldwide access to your EG-PM1W-001, via internet or the free PowerMan app

### Packaging

Q'ty in crtn, pcs	20
Crtn volume, CUM	0.02634825
Crtn weight, kgs	5.1
Individual package size LxWxH:	80x95x160 mm
Carton size LxWxH:	430x285x215 mm
Country of origin	CN
Barcode	8716309076555
Customs code	8544429090

### Package contents

EG-PM1W-001  
User manual and Quick installation guide  
CD with Power Manager software for Windows

### Certificates



### Specifications

Interface: Wireless LAN IEEE 802.11 b/g/n protocols up to 300 Mbps

WLAN repeater mode

Input voltage: up to 250 VAC, 50 – 60 Hz

Maximum load current: 16 A

Maximum power consumption: 2.5 W

Hardware schedule possibilities:

Maximum number of independent hardware schedules 45

Time interval between the events – from 1 minute to 180 days

Loop period in days, hours, minutes or seconds ( single loop period per socket)

Timer accuracy: not more than 2 seconds error per day

Clock synchronisation with NTP server

Dimensions: 108 mm x 76 mm x 55 mm

Net weight: 0.15 kg

### System requirements

Local area network with a WLAN switch/router  
Any Internet-enabled computer connected to the local area network  
Computer running Windows® 2000/XP/Vist/Windows 7/8 is required for using the Power Manager software (use of this software is not compulsory)