

Multipresa con protezione EnerGenie programmabile con interfaccia LAN

EG-PM1W-001



YOUR SWITCH IS MY COMMAND

- EG-PM1W-001 is an easy to use WiFi Smart Home socket with powerful power management options. It enables you to switch the socket on or off via your home WiFi, Internet, by timer schedule, or by programmable special software events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print). With your free personal user account on EnerGenie.com you can manage your EG-PM1W-001 via Internet from all over the world. The practical and easy to use PowerMan app allows you to control the socket from your smartphone.
- Stay in control of all your electric appliances
- Simply switch devices on or off with your smart phone or tablet
- Built-in WiFi repeater function –Optimal WiFi coverage ensured

Caratteristiche

- Accendi e spegni ogni presa individualmente e manualmente dal tuo computer
- Accendi e spegni ogni presa tramite il timer programmabile
- Accendi e spegni ogni presa individualmente al verificarsi di un determinato evento (ad es. se Windows o altri programmi si avviano o terminano, la stampante inizia e termina il proprio lavoro ecc.)
- Grazie all'interfaccia WLAN e al web server incorporato, si può accedere alla EG-PM1W-001 da qualunque computer all'interno della tua rete locale (attraverso un browser Internet)

Confezione

Quantità per cartone, pezzi	20
Volume del cartone, CUM	0.02634825
Peso del cartone, Kg	5.1
Individual package size LxWxH:	80x95x160 mm
Carton size LxWxH:	430x285x215 mm
Paese di origine	CN
Barcode	8716309076555
Customs code	8544429090

Contenuto della Confezione

EG-PM1W-001
User manual and Quick installation guide
CD with Power Manager software for Windows

Certificazioni



Specifiche

Interface: Wireless LAN IEEE 802.11 b/g/n protocols up to 300 Mbps

WLAN repeater mode

Input voltage: up to 250 VAC, 50 – 60 Hz

Maximum load current: 16 A

Maximum power consumption: 2.5 W

Hardware schedule possibilities:

Maximum number of independent hardware schedules 45

Time interval between the events – from 1 minute to 180 days

Loop period in days, hours, minutes or seconds (single loop period per socket)

Timer accuracy: not more than 2 seconds error per day

Clock synchronisation with NTP server

Dimensions: 108 mm x 76 mm x 55 mm

Net weight: 0.15 kg

Requisiti di sistema

Local area network with a WLAN switch/router
Any Internet-enabled computer connected to the local area network
Computer running Windows® 2000/XP/Vist/Windows 7/8 is required for using the Power Manager software (use of this software is not compulsory)