

Multipresa programmabile con interfaccia WLAN

EG-PMS2-WLAN

YOUR SWITCH IS MY COMMAND

- EG-PMS2-WLAN is an advanced surge protector with power management features. It is possible to individually switch 4 sockets on or off manually via your local WiFi network or Internet, by timer schedule, or by programmable special events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print). With your free personal user account on EnerGenie.com you can manage your EG-PMS2-WLAN via Internet from all over the world, even with your smartphone.
- Stay in control of all your electrical devices at home or in the office
- Program four sockets individually via WLAN or Internet
- Switch electric devices on or off with your smartphone, wherever you are
- Protect your valuable equipment
- An advanced standby-killer for computer peripherals
- Perfect solution for security systems , sauna , aquariums, pet habitats, etc.



Caratteristiche

- Accensione e spegnimento manuale di tutte le prese dalla finestra di controllo del software
- Built-in web-server: EG-PMS2-WLAN può essere controllata da qualsiasi computer tramite Internet (con software Internet Explorer o Power manager)

Confezione

Quantità per cartone, pezzi	10
Volume del cartone, CUM	0.04545375
Peso del cartone, Kg	12.47
Individual package size LxWxH:	400x140x60 mm
Carton size LxWxH:	425x345x310 mm
Paese di origine	CN
Barcode	8716309076784
Customs code	8536301090

Contenuto della Confezione

EG-PMS2-WLAN
 USB cable
 WLAN antenna
 User manual and Quick installation guide
 CD with Power Manager software for Windows

Certificazioni



Specifiche

Input voltage: up to 250 VAC, 50 – 60 Hz
 Maximum load current: 10 A
 Maximum power consumption: 3.5 W
 Surge protection: Type3, Up=1.2KV for L-N, Uoc=4KV for L-N Uo=230V
 Uc=250V Ucs=1.1X230V=253V
 Built-in power supply
 Wireless LAN: IEEE 802.11 b/g
 Hardware schedule possibilities:
 Maximum number of independent hardware schedule events – 45 per socket

Time setting accuracy in seconds
 Combine periodical and once events
 Timer accuracy: not more than 2 seconds error per day in case that power is always present. Otherwise there can be an additional up to 2 seconds error per each "power off"
 Indoor use only
 Dimensions: 378 x 98 x 55 mm
 Net weight: up to 1 Kg

Requisiti di sistema

Local area network with a WLAN switch/router
 For the initial setup and Power Manager software: Windows® 2000/XP/Vista or Windows 7/8 computer
 Any Internet-enabled or WiFi-enabled computer or PDA and any Internet-