

Home pure sine inverter with AVR and battery management function, 1000VA

EG-HI-PS1000-01

- Easily combine with any 12V battery for 24/7 Active backup power
- Protects your sensitive and valuable equipment
- Pure sine wave output Perfect for solar panel installations and other sensitive equipment
- Compact and reliable ideal for home and small office use



Caratteristiche

- 1000 VA Pure sinewave Home Inverter with AVR and battery management function
- Can be used as UPS when external 12V battery is connected
- High charging current (up to 15 A), recharges the large capacity batteries quickly
- "Smart charging technology" Intelligent charger for batteries with the "training" mode
- Protection against short circuit, overload, overvoltage or undervoltage
- Modular CPU controlled circuit with self-diagnostics cycle at every start-up

Confezione

Quantità per cartone, pezzi	2
Volume del cartone, CUM	0,049966
Peso del cartone, Kg	21.5
Individual package size LxWxH:	415x198x250 mm
Carton size LxWxH:	430x415x280 mm
Paese di origine	CN
Barcode	8716309087261
Customs code	8504408490

Contenuto della Confezione

Home Inverter
User manual

Specifiche

UPS type: line interactive, pure sinewave
 Input: AC 140-275V, 50Hz/60Hz $\pm 10\%$
 Output: AC 220 V $\pm 10\%$, 50Hz/60Hz $\pm 5\%$ (on battery)
 Switching time: less than 4 ms
 Battery: external, sealed lead-acid 12 VDC, up to 300 Ah (not included)
 Charge time: up to 12 hours
 Sockets: 2 x Schuko output (CEE 7/4)
 Operating conditions: 0°C-40°C, at humidity 10-90%RH non condensing
 Power: 1000 VA (600 W)
 Dimensions: 390 x 160 x 240 mm

Certificazioni

