



4-in-1 car smartphone holder with charger, FM-transmitter and handsfree function

TA-CHU3

- Universal fits most smartphones
- 4-in-1 solution: phone holder, USB charger, audio FM-transmitter and handsfree function
- Fits in standard car cigarette lighter or 12V outlet



Features

- Universal smartphone car holder: adjustable for use with devices from 58 to 85 mm wide
- Built-in USB charger (charging cable is not included)
- FM-transmitter: play your music on your car stereo via FM frequency,
- Handsfree: handle voice call via FM transmitter and built-in mic
- LCD display for easy FM-frequency settings and flexible neck to position your phone at any angle

Packaging

Q'ty in crtn, pcs	40
Crtn volume, CUM	0.095
Crtn weight, kgs	9.92
Individual package size LxWxH:	280x90x75 mm
Carton size LxWxH:	580x410x400 mm
Country of origin	CN
Barcode	8716309100038
Customs code	8504403090

Specifications

DC voltage: 12 24 V input, 5 V DC ± 0.25 V output (max. 3.1 A)

Frequency range: 88.1 ... 107.9 MHz

Idle power consumption: no more than 0.085 W

Over-current protection: if current is > 2 A

Charger working conditions: temperature 0...+40°C, humidity 95%

Net weight: 128 g

Adjustable width: 58 85 mm

Dimensions: 282 x 80 x 98 mm

System requirements

12-24 V DC vehicle cigarette lighter socket

Instructions:

1. Insert the 3.5 mm jack into the phone (device with a 3.5mm socket is required)
2. Check the free frequency in the radio
3. Set the selected radio frequency in the transmitter

Certificates

