



Automatic CPU and audio switch, 4 PCs

CAS-441

- World of ideas
- Enables one set of keyboard/monitor/mouse to control 4 PCs
- Computers selectable by means of a push button or keyboard hot keys
- Also switches audio
- Save space and money in multi-computer environments
- Suitable for any operating system



Χαρακτηριστικά

- Switching of the PCs stereo audio channels
- Optional SwitchSound mode switching of the PCs stereo audio channels
- Additional buzzer and LED indication of the sound event
- Optional HoldSoundEvent mode – indication of the sound event will be continued until the channel is selected
- Plug and Play keyboard and mouse initialization
- Hot-plug connection of the computers without need to reboot
- PC switching via front panel pushbuttons or keyboard hot keys
- No software required

Συσκευασία

Ποσότητα ανά χαρτοκιβώτιο, τμχ	20
Όγκος χαρτοκιβωτίου. CUM	0.046
Βάρος χαρτοκιβωτίου, Kg	16.6
Μέγεθος ατομικής συσκευασίας LxWxH:	255x54x145 mm
Διαστάσεις χαρτοκιβωτίου LxWxH:	300x500x310 mm
Χώρα προέλευσης	CN
Barcode	8716309026062
Τελωνειακός κώδικας	8536508090

Προδιαγραφές

Number of switching computers: 4
 Mouse and keyboard protocol emulation: PS/2 keyboard, PS/2 mouse, PC/AT keyboard
 Case design: Desktop
 Case housing: Metal with plastic front panel
 Computer selection: Push buttons or keyboard hot keys
 Computer side connectors: HD-15Mx4, MD-6Fx8, 3.5 mm stereo audio jack x 4
 Console side connectors: HD-15Mx1, MD-6Fx2, 3.5 mm stereo audio jack x 1
 Front panel LEDs per channel: "Link/Event", "Active/Scan"

Audio channels type: Stereo

Απαιτήσεις συστήματος

Console requirements:
 VGA, SVGA, or Multisync monitor supporting the highest resolution among all the PCs connected to the switch
 PS/2 compatible mouse
 PS/2 compatible keyboard
 Computers requirements:
 VGA, SVGA or Multisync video card

Πιστοποιητικά

