

EnerGenie Programmable surge protector

EG-PMS

YOUR SWITCH IS MY COMMAND

- EG-PMS is an advanced surge protector with power management features. It is possible to individually switch 4 sockets on or off manually via your PC, by timer schedule, or by programmable special events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print)
- Stay in control of all your electrical devices at home or in the office
- Program four sockets individually via your PC or laptop
- Protect your valuable equipment
- An advanced standby-killer for computer peripherals



Features

- Switch individual sockets on/off manually from your computer
- Switch individual sockets on/off by a programmable timer schedule
- Switch individual sockets on/off whenever a certain software event occurs (e.g. Windows/other software start-up/shutdown, print spooler starting and finishing its job, etc)
- Timers stays active even when the managing PC is turned off
- Child protected sockets
- Mounting holes

Packaging

Q'ty in crtn, pcs	10
Crtn volume, CUM	0.048645
Crtn weight, kgs	13.2
Individual package size LxWxH:	465x145x65 mm
Carton size LxWxH:	470x300x345 mm
Country of origin	CN
Barcode	8716309070256
Customs code	8544429090

Package contents

- EG-PMS
- User manual
- USB cable
- CD with Power Manager software for Windows

Specifications

- Input voltage 220 – 230 VAC~ 50 – 60 Hz
- Maximum load current 10A
- Maximum current consumed by the EG-PMS from the computer USB port: 350mA
- Maximum quantity of EG-PM connected to one computer at the same time: no restrictions (only restricted by the maximum allowed quantity of the USB devices)
- Plug and Play
- Hardware schedule restrictions:
- Maximum number of independent hardware schedules: 16 pcs
- Time interval between the events: from 1 minute to 180 days
- Timer accuracy: not more than 3 seconds error per day

Certificates

