

Stekkerdoos met overspanningsbeveiliging

EG-SP5-U6B-RM

- Bescherm je waardevolle apparatuur! Met draadloze afstandsbediening! Laadt ook de meeste mobiele telefoons en MP3-spelers!



Kenmerken

- Vijfvoudige gearde stekkerdoos met overspanningsbeveiliging en afstandsbediening
- Beveiligt computers en andere waardevolle apparatuur tegen schadelijke stroom en spanningspieken
- USB poorten (5 V, 2 A) voor het opladen van al uw USB-apparaten
- Geschikt voor belastingen tot 16 A
- Hoogwaardige vlamvertragende kunststof behuizing
- Kindveilige stopcontacten
- Montagegaten, voor eenvoudige wandmontage

Verpakking

Verpakkingshoeveelheid/stuks	10
Volume doos/CUM	0.0366
Gewicht doos/kg	9.6
Afmetingen productverpakking LxBxH:	455x112x58 mm
Afmetingen transportverpakking LxBxH:	480x305x250 mm
Land van herkomst	CN
Streepjescode	8716309070966
Douanecode	8544429090

Inhoud verpakking

Surge protector
Remote control with a battery (12 VDC, type 27A)

Specificaties

Maximum total power load: 250 V AC, up to 16 A, 50 Hz
Remote control: up to 10 m
Sockets: German (Schuko) type
Plug: built-in German (Schuko) 16 A, 1.8 m cord
USB ports: 2 pcs, 5 V DC, total current up to 2 A
Surge protection: $U_p = 1.2 \text{ kV}$ for L-N, L-G, N-G; $U_{oc} = 4 \text{ kV}$ for L-N, L-G, N-G; $U_o = 230 \text{ V}$, $U_c = 250 \text{ V}$, $U_{cs} = 1.1 \times 230 = 253 \text{ V}$

Standby power: 0.6 W
Cable length: 1.8 m
Dimensions: 421 mm x 61 mm x 44 mm

Certificaat/Certificaten

