

Priza Programabila cu protectie EnerGenie

EG-PMS2

YOUR SWITCH IS MY COMMAND

- EG-PMS2 is an advanced surge protector with power management features. It is possible to individually switch 4 sockets on or off manually via your PC, by timer schedule, or by programmable special events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print)
- Stay in control of all your electrical devices at home or in the office
- Program four sockets individually via your PC or laptop
- Protect your valuable equipment
- An advanced standby-killer for computer peripherals



Features

- Comutarea individuala a prizelor on/off manual din computer
- Comutarea individuala a prizelor on/off de catre un programator de timp
- Comutarea individuala a prizelor on/off oricand exista un eveniment software (ex: cand Windows-ul/alte soft-uri se deschid/inchid, cand print spooler-ul isi incepe si isi termina activitatea, etc)
- Include filtru de zgomot cu frecventa radio (EMI/RFI filter), absoarbe 99% din zgomot in stadiul de alimentare si prelungeste viata echipamentelor electrice.

Packaging

Q'ty in crtn, pcs	10
Crtn volume, CUM	0.04413625
Crtn weight, kgs	12.8
Individual package size LxWxH:	465x145x65 mm
Carton size LxWxH:	425x335x310 mm
Country of origin	CN
Barcode	8716309074155
Customs code	8536301000

Package contents

EG-PMS2
User manual
USB cable
CD with Power Manager software for Windows

Certificates



Specifications

Input voltage 220 – 230 VAC~ 50 – 60 Hz
Maximum load current 10A
Maximum current consumed by the EG-PMS2 from the computer USB port: 350mA
Maximum quantity of EG-PMS2 connected to one computer at the same time: no restrictions (only restricted by the maximum allowed quantity of the USB devices)
Plug and Play
Hardware schedule restrictions:
Maximum number of independent hardware schedules: 16 pcs
Time interval between the events: from 1 minute to 180 days

Timer accuracy: not more than 3 seconds error per day
Working temperature range: from +10 to +40 degrees Celsius

Dimensions: 378 x 98 x 55 mm
Net weight: not more than 1.3 kg

System requirements

Computer running Windows 7/8/10/11 is required for using the Power Manager software
A free USB port