

EnerGenie Programmable power strip

EG-PM2

YOUR SWITCH IS MY COMMAND

- EG-PM2 is a power outlet strip with advanced power management features. It is possible to individually switch 4 sockets on or off manually via your PC, by timer schedule, or by programmable special events (eg: switch on my scanner whenever I start Photoshop, or have my printer switched on only when I really print)
- Stay in control of all your electrical devices at home or in the office
- Program four sockets individually via your PC or laptop
- An advanced standby-killer for computer peripherals



Features

- Switch individual sockets on/off manually from your computer
- Switch individual sockets on/off by a programmable timer schedule
- Switch individual sockets on/off whenever a certain software event occurs (e.g. Windows/other software start-up/shutdown, print spooler starting and finishing its job, etc)
- Timers stays active even when the managing PC is turned off
- Child protected sockets
- Mounting holes

Packaging

Q'ty in crtn, pcs	10
Crtn volume, CUM	0.0459885
Crtn weight, kgs	12.8
Individual package size LxWxH:	465x145x65 mm
Carton size LxWxH:	430x345x310 mm
Country of origin	CN
Barcode	8716309075565
Customs code	8544429090

Package contents

- EG-PM2
- User manual
- USB cable
- CD with Power Manager software for Windows

Specifications

Input voltage: up to 250 VAC, 50 – 60 Hz
 Maximum load current: 10 A
 Maximum power consumption: 3.5 W
 Built-in power supply
 Hardware schedule possibilities:
 Maximum number of independent hardware schedules 16
 Time interval between the events – from 1 minute to 180 days

Timer accuracy: not more than 2 seconds error per day
 Working temperature range: 0 40 Celsius degrees
 Dimensions: 378 x 98 x 55 mm

Certificates

