

# 150W Convertisseur pour automobile du courant continu en courant alternatif

EG-PWC-031

- Pour utiliser d'avantage d'appareils dans votre voiture



## Propriétés

- Fournit du courant alternatif à 220V dans votre auto
- Pour faire fonctionner tous vos appareils à courant alternatif, fournit une alimentation de 150W : ordinateur portable, chargeur pour téléphones portables ou caméras, aspirateurs, et autres appareils électriques
- Une protection court-circuit et surcharge, et un ventilateur intégré vous garantissent une bonne stabilité du convertisseur

## Packaging

Q'ty in crtn, pcs	30
Crtn volume, CUM	0.10773
Crtn weight, kgs	16.7
Individual package size LxWxH:	260x160x80 mm
Carton size LxWxH:	630x450x380 mm
Country of origin	CN
Barcode	8716309075916
Customs code	8504408590

## Contenu du colis

Car power inverter  
User manual

## Spécificités

Input: 11-15 VDC (car cigarette lighter)  
Output: 230 VAC +/-10% at 50 Hz (+/-3Hz), modified sine wave,  
Power output: 150 W continuous power (peak power 300 W)  
USB power output: 5 V / 1 A  
Recommended operating temperature: +5...+35 °C (max -15...+50 °C)  
Material: aluminium and plastic  
Cable: 600 mm (cigarette lighter cable, 1.5 sq.mm)  
Dimensions: 150 x 70 x 70 mm  
Net weight: 470 g

## Certificats

