



Manual
switching power
distribution unit

English:
Manual power distribution unit (PDU),
8 sockets, 1U, 16A
8 x German Schuko type sockets
Sockets with safety shutters
1U rack mountable

Deutsch:
8-fach Steckplätze, 1U, 16 A
8-fach Stromverteiler mit Safety-Shutter
Geerdete Anschlüsse mit Safety-Shutter
Passend zur Montage in 19" Racks (1U)

Українська:
8-полюсний розподільчий блок живлення в стійку 19" 1U,
8 вихідних євро-розеток
8 шт. захисних шторок безпеки
Розмір 1U в 19-ти дюймову стійку

Русский:
Разветвитель питания в стойку 19" 1U,
8 евро-розеток
8 выходов евро-розеток
Шторки безопасности
Размер 1U в 19-ти дюймовую стойку

Made in China

www.energenie.com
PURE POWER
EG-PDU-012
8-7163091082495

Nederlands:
19" steekkerdoos met schakelaar (PDU),
8-voudig, 1U, 16 A
8-voudige professionele steekkerdoos met geaarde stopcontacten
Eenvoudig te monteren in 19" rack (1U)

Français:
Adaptateur Multi prises PRO,
8 prises, 1U, 16 A
8 x Prises type Schuko
Avec système de sécurité
Convient au rack type 1U et autres ...

System requirements:
Input: 1 pcs, german Schuko type, female
Output: 8 pcs, german Schuko type, male, 2 m power cord (3 x 1.5 mm²)
Max. output current: 16 A
Max. output power: up to 3680 W
Frequency: 50 Hz
Shell: aluminium
Temperature: 0 °C ~ 45 °C
Humidity: 0 % ~ 90 %
Dimensions: 432 mm x 44 mm x 44 mm
Net weight: 0.8 kg

Note: indoor use only

Manual
switching power
distribution unit



Manual switching power distribution unit



Manual switching power distribution unit

- Professional aluminium power supply unit
- Rack mountable - ideal for server cabinets

Manual switching power distribution unit

size: 550x95x55 mm